LENTO

House of Green Energy



Li-ion Series

Lithium

BATTERY INVERTER

SALIENT FEATURES

- ECO Friendly
- Dynamic control algorithm based BMS ensure safety of Lithium Battery
- Elegant & Compact Design
- Light weight so wall mountable
- Long Life of Battery 6-7 years
- Fast Charging
- Maintenance Free
- Inbuilt LiFepo4 Battery inside
- Resettable CKT Breaker
- Grid Charging Enable/Disable

LENTO
House of Green Energy

Lithium BATTERY INVERTER

Li-ion Series Specification

S.No.	Parameter	Unit	Rating	
	Model Name		**1100/12V**	**2100/24V**
1	System Rating	VA	1100	2100
2	Full Load Input Current ±2A	Amp	65	65
3	Operating DC Voltage	V	12.8	25.6
4	Input Voltage max Voc (PV)	Vdc	25	45
5	Maximum Solar Array Power (PV)	Wp	1000	2000
6	Battery	V	12.8V 100AH Life Po4	25.6V 100AH Life Po4
7	Capacity		1.280kWH	2.58kWH
8	Backup Time @400W Load	Hr	3 Hr / 6 Hr	
9	Backup Time @ 100% Load	Hr	1 Hr 30 min	
10	Battery Life	Yr	PWM	
11	Type of Solar Charger		>90	
12	Efficiency of SCC	%	220V + 7V	
13	Nominal Output voltage in inverter mode	Vac	–	
14	Output Supply Phases		Single	
15	Nominal Output Frequency of Inverter	Hz	50 ± 1	
16	Output Voltage Regulation 10.8-14.4V	%	180-220	
17	Creast Factor		3:01	
18	Overload Capacity 125%	Sec	6 (6 Retry)	
19	Overload Capacity 150%	Sec	2 (6 Retry)	
20	Battery Low Voltage alarm per Battery	Vdc	10.8 ± 0.2	
21	Battery Low Voltage cut per Battery	Vdc	10.6 ± 0.2 (With 4 Retry)	
22	Batter Low cut recovery per Battery through Solar	Vdc	12.8 ± 0.2 (or Mains or Reset Swich on Front Panel)	
23	Max Battery Charging Voltage by grid per Battery	Vdc	14.0/28.0 ± 0.2	
24	Max Battery Charging Current by grid in Hi/Lo option	Adc	16A ±2A	
25	Max Battery Charging Voltage by Solar per Battery	Vdc	14.0/28.0 ± 0.2	
26	Max Battery Charging Reconnect Voltage by Solar and Grid per Battery with LiPo4 Battery		13.6 ± 0.2	
27	Battery High Cut with Alarm per Battery	Vdc	15.5 ± 0.2	
28	Battery High Cut Recovery per Battery	Vdc	14.5 ± 0.2	
29	Max Battery charging Current by Solar	Adc	30 ± 2A	
30	Max Charging Current to Battery by Solar+Grid	Adc	30 ± 2A	
31	Grid Low Cut Voltage (IT load/Normal load)	Vac	180/100 ± 10	
32	Grid Low Cut Voltage recovery (IT load/Normal load)	Vac	190/110 ± 10	
33	Grid High Cut Voltage (IT load/Normal load)	Vac	265/280 ± 10	
34	Grid High Cut Voltage Recovery (IT load/Normal load)		255/270 ± 10	
35	Grid charging Enable/Disable	Vac	Yes	
36	Selection of UPS Load/Normal Load		Yes	
37	Selection of Operating Mode		HC-Charging current = 30A ±1A Solar + Mains till battery boost voltage with maximum Solar Sharing. System will not be disconnect Grid in any case	
			EC-Charging current= 30A ±1A Solar + Mains till boost voltage, System will cut off the mains when battery voltage reaches boost voltage level and output load is transferred to Solar + Battery and Grid reconnected <=11.8V/11.2V per Battery.	
			SC-Charging current= 20A ±1A Solar + Mains till boost voltage, System will cut off the mains when battery voltage reaches boost voltage level and output load is transferred to Solar + Battery and Grid reconnected <=12.0V per Battery or Solar fails or if Solar <5A check if Solar < discharging connect grid	
38	Output Voltage at No load at rated Battery Voltage	Vac	220 ± 2	
39	Input current at no load at Nominal Battery Voltage	Adc	2.4 ± 0.2	
40	Noise @ 1 meter	dB	<50	
41	Protections		Overload, Battery Deep Discharge, Battery Overcharge, Short circuit(1retry), Battery Hi, PV Reverse, Over Temp, Fuse Trip, Battery reverse	
42	LCD Display Parameters		PV Current, Battery Voltage, Mains Voltage, UPS ON/OFF, UPS Mode, Solar Available, Load percentage (0 to 150%), Over Load, Short ckt, Fault, Battery Low, Over Temp, PV Reverse, Fuse Trip,	
43	Indication LEDs		Tact Switch Status	
44	Operating Temperature Range	°C	0-50	
45	Storage Temperature Range	°C	0 +65	
46	Max RH	%	95	
47	Front Panel details (MCB, Display, Selection Switch etc)		Display with Tact Switch	
48	Changeover time from Inverter to Mains in UPS mode	ms	<10	
49	Changeover time from Inverter to Mains in Normal mode	ms	<10	
50	Changeover time from Mains to Inverter in UPS mode	ms	<10	
51	Changeover time from Mains to Inverter in Normal Mode	ms	<40	
52	Input Protection		Resettable Circuit breaker	
53	Installation Type		Wall Mount	

3Y
BATTERY LIFE FAST CHARGING

COMPACT SIZE & LESS WEIGHT

MAINTENANCE FREE

FAST CHARGING

HIGHER BACK UP

LONGER LIFE

LENTO INDUSTRIES PVT. LTD.
Registerd office : 05, Ground Floor, Plot No. 556,
School Block, Shakarpur Delhi-110092
Manufacturing Unit
A - 27, Sector-58, Noida, Gautam Buddha Nagar, Uttar Pradesh - 201301
Tel : +91-8527476197, Email : info@lentoindia.com

MADE IN INDIA